

**TECHNICAL PARAMETERS Amplifier A 6 00 11 378**

Max. output power <sub>RMS</sub>	195000 VA
Frequency range	DC - 5000 Hz
Voltage <sub>RMS</sub> max.	±212 V
Current <sub>RMS</sub> max.	1800 A
Signal input voltage <sub>RMS</sub>	10 V
Total Harmonic Distortion (at 70A <sub>RMS</sub> , 200 Hz)	< 0.2 %
Signal to noise ratio	> 80 dB
Power supply - Amplifier	3~ / N / PE 400 V±5% 50 Hz, Direct connection
Power supply - Field power supply unit	3~ / N / PE 400 V±5% 50 Hz, Direct connection
Max. power consumption at 400 V - Amplifier	244 kVA (at operation with vibration test system TV 59416)
Max. power consumption at 400 V - Field power supply	98 kVA
Recommended fuse protection - Amplifier	450 A slow (for full extension)
Recommended fuse protection - Field power supply	200 A slow
Dimensions (WxHxD) - Amplifier	2400 x 2200 x 900 mm
Dimensions (WxHxD) - Field power supply	1200 x 1740 x 850 mm
Total mass - Amplifier	2500 kg
Total mass - Field power supply	1135 kg
Interlocks:	Overload, temperature, displacement, compressed air, phase monitoring, differential pressure, water flow rate, conductance, emergency stop

Features:

- TIRA Digital amplifiers can be adapted to almost all shakers existing on the market
- Flexible in output power due to modular design
- Low distortion factor of up to < 0.2 %
- High clock frequency power modules of 102 kHz ±5%
- Multifunctional LC-touch screen display
- Error indication and system parameters are shown in plain text
- Safety management monitors interlocks of the vibration test system
- Inputs for additional safety functions from external sources
- Adjustable current limit
- Adjustable output voltage offset
- Integrated mains switch and line filter
- Field voltage/current variable according to customer specification
- 4 Sigma peak current
- Lo-Field/Hi-Field (Energy-saving mode)



Amplifier (illustration similar)



Field power supply