

TECHNICAL PARAMETERS Amplifier BAA 1000-E

Max. output power _{RMS}	1200 VA
Frequency range	2 Hz - 20 kHz
Voltage _{RMS} , max.	72 V
Current _{RMS} , max.	18 A
Signal input voltage _{RMS}	< 5 V
Distortion factor	< 0.1 %
Signal to noise ratio	> 90 dB
Field power supply (FPS)	yes (external)
Field voltage, max.	70 V
Field current, max.	3.2 A
Weight (Amplifier+FPS)	57 kg
Dimensions (Amplifier+FPS) (WxHxD)	483 x 293 x 585 mm
Power supply (Amplifier)	1~ / N / PE 230 V±5% 50 Hz, CEE 7/7
Power supply (FPS)	1~ / N / PE 230 V±5% 50 Hz, CEE 7/7
Recommended fuse protection	each 16 A slow
Max. power consumption at 230 V (Amplifier)	1.4 kVA
Max. power consumption at 230 V (FPS+Blower)	2.4 kVA
(at operation with vibration test system TV 5220-120)	
Interlocks:	Overload, temperature, clipping and more

Features:

TIRA analog amplifiers can be adapted to all permanent magnet driven shakers on the market
 High Signal to noise ratio of >90 dB
 Low distortion factor of < 0.1 %
 Backgroundlit multifunctional display
 Safety management system monitors functions as temperature, overcurrent and overtravel
 Selectable mains voltage range (Adjustment 100 V, 120 V or 230 V factory preset)
 Operation switchable in current or voltage mode
 Adjustable current limit
 Phasing between input- and output signal turnable
 Power cable length 1.5 m with CEE 7/7 connector

